

MODEL: LS-806 “STRIKER”

**10 WATT LED ALUMINIUM ALLOY RECHARGEABLE FLASHLIGHT WITH
INTERCHANGEABLE POWER SOURCE OPTIONS**



PHYSICAL AND MECHANICAL DATA

SIZE IN MILLIMETRES	WEIGHT	PACKAGING	LIGHT SOURCE
Head Width : 41 mm Body Width : 32 mm Length : 150 mm	180 Gram (without battery)	Box	10W, L2 Cree LED 750 Lumen

POWER SOURCE

1. Rechargeable 18650 Lithium-ion battery (3,7V – 2,600 mAh) – (Minimum charge cycles: 700) OR;
2. Rechargeable 26650 Lithium-ion battery (3.7V – 5200 mAh) - (Minimum charge cycles: 700) OR;
3. 3 x AAA Disposable batteries – batteries not included (Alkaline recommended)

With option 1 + 2 above, a 3 x AAA disposable battery holder is included, for a non-rechargeable option

ACCESSORIES INCLUDED (WITH RECHARGEABLE OPTION)

1x 18650 Lithium-ion 3,7V 2,600 mAh with battery sleeve	Charge Control Cable	3 x AAA battery holder (disposable batteries not included)	External battery charger
			

OPTIONAL ACCESSORIES

DC 12V USB Car Adaptor USB	26650 Lithium-ion 3,7V 5200 mAh	Pouch	USB Wall Adaptor
			

SPECIFICATIONS: (When Battery is fully charged)

With 18650 battery: (3.7V – 2200 mAh)	With 3 x AAA Disposable batteries (Alkaline)
• Constant Burn Time at 100% : 2.5 hrs • Constant Burn Time at 50% : 4 hrs • Constant Burn Time at 25% : 10 hrs • Constant Burn Time Strobng : 2.5 hrs • Constant Burn Time SOS : 2.5 hrs	• Constant Burn Time at 100% : 30 min • Constant Burn Time at 50% : 1 hr • Constant Burn Time at 25% : 1.5 hr • Constant Burn Time Strobng : 30 min • Constant Burn Time SOS : 30 min

FEATURES

- 5 Mode Settings: 100% - 50% - 25% - Strobng - SOS
- Super Strong Aluminium Alloy Body
- Hard Anodising (Black)
- Cree LED – 100,000 hr Lifetime
- Lasts much longer than conventional incandescent globes
- New built in energy management system, results in longer battery life
- Highly improved reflector providing a concentrated focussed spot
- Impact resistant: Drop – 1,5m
- Weather Resistant
- Beam Distance: 300m (Pre focused)

APPLICATION

- A rugged flashlight to use in all conditions and circumstances, robust enough to deal with rough handling and falling.
- The disorienting strobe effect allows the user to deal with violent individuals in dangerous low light and dark conditions.

OPERATING INSTRUCTIONS

- Press Switch Button Once: 100% Brightness
- Press Switch Button Again: 50% Brightness
- Press Switch Button Again: 25% Brightness
- Press Switch Button Again: Disorientating Strobe (100% Brightness)
- Press Switch Button Again: SOS
- Press Switch Button Again: Off

CHARGING INSTRUCTIONS

Very Important:

- Always switch flashlight off during charging.

- Remove battery from flashlight and insert into external battery charger, observing the correct polarity.
- Insert male plug of USB charge cable into female socket in external battery charger.
- Insert USB connector (plug) of charge cable into either AC Adaptor, DC Adaptor or computer USB port.
- The LED power indicator in battery charger will show RED continuously to indicate that power is on
- Charge time: 5 hours
- Over time, unused batteries will discharge and must be recharged before use.
- Use batteries only for intended purpose.
- Disconnect chargers from power sources when not in use.
- Do not leave flashlight unattended while ON

CAUTION: Total discharge of battery (totally flat) is dangerous and will shorten battery life

